

32-channel IP Recorder

NVR-6332P16-H4/F





FUNCTIONS













...×2













- •16 x PoE Ethernet ports
- •32 x video and audio channels
- •Recording speed up to 960 fps at 3840 x 2160 •Supports resolution up to 3840 x 2160
- •Recorded stream size: 256 Mb/s in total
- from all cameras •4 x internal place for HDD mounting
- •2 x monitor outputs (HDMI 4K UltraHD, VGA)
- •RACK mount
- Face recognition

DIMENSIONS



440 mm





Operating system

Operating Temperature

The recorder is dedicated to work with NOVUS 6000 series IP cameras. Detailed data can be found in the compatibility table available in the DOWNLOADABLE FILES tab.

| IP Cameras | up to 32 channels at 3840 x 2160 resolution (video + audio) |
|-------------------------------------|--|
| Maximum Supported Camera Resolution | 3840 x 2160 |
| Compression | H.264, H.265, H.265+, H.265 Smart |
| Monitor Output | $main \ (split \ screen, \ full \ screen, \ sequence): 1 \ x \ HDMI \ (4K \ UltraHD), 1 \ x \ VGA \ (up \ to \ 2 \ monitors \ simultaneously \ to \ t$ |
| Dualstreaming Support | yes |
| Fisheye Support | yes, 6000 IP series cameras using NVR, Internet Explorer, SuperLive Plus, N Control 6000 |
| Audio | |
| Audio Input/Output | 1 x line-in (RCA) / 1 x HDMI, 1 x line-out (RCA) |
| Recording | |
| Stream Size | 256 Mb/s in total from all cameras |
| Recording Mode | continuous, triggered by: manual, alarm input, motion detection, face recognition, intelligent image analysi functions |
| Prealarm/Postalarm | up to 5 s/up to 600 s |
| Display | |
| Display Speed | 960 fps (32 x 30 fps) |
| Playback | |
| Playback Speed | 480 fps (16 x 30 fps) |
| Recorded Data Search | by date/time, events, image analysis events, POS, motion in a defined area, related to face recognition, tags, license plate number |
| Backup | |
| Backup Methods | USB port (HDD or Flash memory), network |
| Backup File Format | MP4, AVI, RPAS (player included) |
| Storage | |
| Internal Storage | available mount: 4 x HDD 3.5" 14 TB SATA |
| Total Internal Capacity | 56 TB |
| Alarm | |
| Internal Alarm Input/Output | 16/4 relay type |
| Camera Alarm Input/Output | supports IP camera's alarm input/output |
| Motion Detection | supports camera's motion detection |
| System Reaction to Alarm Events | buzzer, alarm output activation, recording activation, PTZ, e-mail with atatchment, Full Screen, PUSH message, voice prompt, snapshot |
| Intelligent image analysis | |
| | |

Exception, Scene Change, Video Blurred, Video Color Cast, Tripwire, Zone entrance, Abandoned Object, Object Disappearance, Face Recognition, Perimeter Intrusion Detection by pedestrian or vehicle, Line Cr Detection by pedestrian or vehicle, License Plate Recognition (LPR) Supported Functions 1000 license plates Database Capacity $1\ x$ Ethernet - RJ-45 interface, 10/100/1000 Mbit/s $16\ x$ Ethernet PoE (IEEE802.3af, Class 3) - RJ-45 interface, 10/100 Mbit/s HTTP, TCP/IP, IPv4/v6, HTTPS, FTP, DHCP, DNS, DDNS, NTP, RTSP, UPnP, SNMP, PPPoE, SMTP, P2P, POS, HTMLS Network Protocols Support NOVUS MANAGEMENT SYSTEM VSS, NOVUS MANAGEMENT SYSTEM AC, NMS, Internet Explorer, Firefox Chrome, Opera, N Control 6000, Edge/Safari, N Control 6000 PC/MAC Software SuperLive Plus (iPhone, Android) Number of Simultaneous Connection up to 10 clients, up to 36 main streams or 128 substreams or 16 playback streams in total Bandwidth 256 Mb/s in total to all client workstations PTZ PTZ Functions pan/tilt/zoom, preset commands Auxiliary Interfaces USB Ports 1 x USB 2.0, 1 x USB 3.0

-10°C ~ 50°C

Operating System Linux Control PC mouse and IR remote controller (in-set included), network System Diagnostic automatic control of: HDDs, network, camera connection loss password protection, IP filtering, MAC filtering, ARP guard

440 (W) x 70 (H) x 390 (D) Weight 4.4 kg (without HDD) 100 ~ 240 VAC Power Supply 60 W (with 4 HDDs) + 246 W PoE

The availability of individual functions (including image analysis) depends on the model of the cameras used, as well as the software version of the recorder and cameras. In order to create face recognition system, piease deploy NOVIS 5000 series IP cameras with "F" in the model name. Presented display and playbacks speeds are achieved using dual-streaming. Detailed data on hard drives can be found in the compatibility table available in the DOWNLOADABLE FILES tab