NOVUS

32-channel IP Recorder

NVR-6432-H2/F





FUNCTIONS



The recorder is dedicated to work with NOVUS 6000 series IP cameras. Detailed data can be found in the compatibility table available in the DOWNLOADABLE FILES tab.





4K HDMI














KEY FEATURES

- •32 x video and audio channels
- •Recording speed up to 960 fps at 4000 x
- •Recorded stream size: 192 Mb/s in total from all cameras
- •2 x internal place for HDD mounting •2 x monitor outputs (HDMI 4K UltraHD, VGA)
- •RACK mount
 •Face recognition

DIMENSIONS





Power Supply

Video	
IP Cameras	up to 32 channels at 4000 x 3000 resolution (video + audio)
Maximum Supported Camera Resolution	4000 x 3000
Compression	H.264, H.265, H.265+, H.265 Smart
Monitor Output	main (split screen, full screen, sequence): $1 \times HDMI$ (4K UltraHD), $1 \times VGA$ (up to 2 monitors simultaneously) spot: $1 \times HDMI$ (FullHD)
Dualstreaming Support	yes
Fisheye Support	yes, 6000 IP series cameras using any web browser, N-VID6, N Control 6000
Audio	
Audio Input/Output	1 x line-in (RCA) / 1 x line-out (RCA), 1 x HDMI
Recording	
Stream Size	192 Mb/s in total from all cameras
Recording Mode	continuous, triggered by: manual, alarm input, motion detection, face recognition, intelligent image analysis functions
Prealarm/Postalarm	up to 5 s/up to 600 s
Display	
Display Speed	960 fps (32 x 30 fps)
Playback	
Playback Speed	480 fps (16 x 30 fps)
Recorded Data Search	by date/time, events, image analysis events, POS, motion in a defined area, related to face recognition, tags, license plate number
Backup	
Backup Methods	USB port (HDD or Flash memory), network
Backup File Format	MP4, AVI, RPAS (player included)
Storage	
Internal Storage	available mount: 2 x HDD 3.5" 10 TB SATA
Total Internal Capacity	20 TB
Alarm	
Internal Alarm Input/Output	8/4 relay type
Camera Alarm Input/Output	supports IP camera's alarm input/output
Motion Detection	supports camera's motion detection
System Reaction to Alarm Events	buzzer, alarm output activation, recording activation, PTZ, e-mail with atatchment, Full Screen, PUSH message, voice prompt, snapshot
lotalliand local and local	

Supported Functions Database Capacity face recognition for 6 NOVUS 6000 series IP cameras with 'F' in the model name or 2 ONVIF cameras Network Interface 2 x Ethernet - RJ-45 interface, 10/100/1000 Mbit/s HTTP, TCP/IP, IPv4/v6, HTTPS, FTP, DHCP, DNS, DDNS, NTP, RTSP, UPnP, SNMP, IEEE 802.1X, PPPoE, SMTP, P2P, P0S, HTML5 Network Protocols Support NOVUS MANAGEMENT SYSTEM VSS, NOVUS MANAGEMENT SYSTEM AC, NMS, Internet Explorer, Firefox, Chrome, Opera, N Control 6000, Edge/Safari, N Control 6000 PC/MAC Software Mobile applications SuperLive Plus (iPhone, Android) Bandwidth 192 Mb/s in total to all client workstations PTZ PTZ Functions pan/tilt/zoom, preset commands Auxiliary Interfaces

USB Ports 2 x USB 2.0, 1 x USB 3.0 Operating system Operating System OSD languages: Polish, English, others

Control PC mouse and IR remote controller (in-set included), network System Diagnostic automatic control of: HDDs, network, camera connection loss password protection, IP filtering, MAC filtering, ARP guard Security 380 (W) x 53 (H) x 268 (D) Dimensions (mm)

40 W (with 2 HDDs) Power Consumption Operating Temperature -10°C ~ 50°C RACK Mount 19" 2U

1.5 kg (without HDD)

12 VDC (100 ~ 240 VAC/12 VDC PSU in-set included)