NoVus

5 MPX IP Camera with video content analysis based on Deep Learning

NVIP-5H-6511/F

6000 VSS

FUNCTIONS



KEY FEATURES

• Resolution: 5 MPX • Lens: fixed focal, f=2.8 mm/F1.6 • Human/Vehicle Object Classification • D/N function - IR cut filter • Video content analysis based on Deep Learning • microSD card support • WDR with double scan sensor • Min. Illumination: 0.009 lx (0 lx, IR on) • IR LED, range up to 50 m

DIMENSIONS





220 mm



NOVUS

6

The camera is dedicated to work with NOVUS 6000 series recorders. Detailed data can be found in the compatibility table available in the DOWNLOADABLE FILES tab.

| | Image | |
|-------|---|---|
| | Image Sensor | 5 MPX CMOS sensor 1/2.7" OmniVision |
| | Number of Effective Pixels | 2688 (H) x 1944 (V) |
| | | 0.009 lx/F1.6 - color mode, |
| | Min. Illumination | 0 Ix (IR on) - B/W mode |
| | Electronic Shutter | auto/manual: 1/3 s ~ 1/10000 s |
| | Digital Slow Shutter (DSS) | up to 1/3 s |
| | Wide Dynamic Range (WDR) | yes (double scan sensor), 120dB |
| | Digital Noise Reduction (DNR) | 2D, 3D |
| | Defog Function (F-DNR) | yes |
| | Highlight Compensation (HLC) | yes |
| | Back Light Compensation (BLC) | yes |
| | Reduction of image flicker (Antiflicker) | yes |
| | Lens | |
| | Lens Type | fixed focal, f=2.8 mm/F1.6 |
| | Day/Night | |
| | | mechanical IR cut filter |
| | Switching Type Switching Mode | auto, manual, time |
| | Switching Mode Switching Level Adjustment | auto, manual, time ves |
| | Switching Level Adjustment Switching Delay | yes 2 ~ 120 s |
| | Switching Delay Switching Schedule | |
| | Visible Light Sensor | yes |
| | - | yes |
| | Network | |
| | Stream Resolution | 2560 x 1440 (QHD), 2592 x 1520, 2592 x 1944, 2304 x 1296, 1920 x 1080 (Full HD), 1280 x 720 (HD), 704 576, 704 x 480, 352 x 288 (CIF), 352 x 240, 480 x 240 |
| | Frame Rate | 30 fps for, 60 fps for and lower resolutions |
| | Multistreaming Mode | number of streams: 3 |
| | Video/Audio Compression | H.264, H.264+, H.264 Smart, H.265, H.265+, H.265 Smart, MJPEG/G.711 |
| | Number of Simultaneous Connections | max. 10 |
| | Bandwidth | 60 Mb/s in total |
| | Network Protocols Support | HTTP, TCP/IP, IPV4, IPV4/V6, UDP, HTTPS, FTP, DHCP, DDNS, NTP, RTSP, RTP, UPnP, SNMP, QoS, IEEE 802.1X, PPPoE, SMTP, RTCP, ICMP, SSL/TLS |
| | Camera Configuration | from Internet Explorer browser Ianguages: Polish, English, Russian, and others |
| | Compatible Software | NOVUS MANAGEMENT SYSTEM VSS, NOVUS MANAGEMENT SYSTEM AC, N Control 6000 |
| | Mobile applications | SuperLive Plus (iPhone, Android) |
| | Video Analytics | |
| | | tamper, line cross, zone entrance, zone exit, object counting, multi loiter, face detection, pedestrian |
| 81 mm | Functions | detection, cross counting, heat map, scene change, video blurred, video color cast, objects distinguishing, people counting, vehicle counting, target counting by area |
| | Other functions | |
| | Privacy Zones | 4 video mask type: single color |
| | Motion Detection | yes |
| | Region of interest (ROI) | 8 |
| | Image Processing | 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction |
| | Prealarm/Postalarm | up to 6 s/up to 120 s |
| | System Reaction to Alarm Events | e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card |
| | Restoring default settings | via web browser, using reset button, via NMS IPTool software |
| | IR LED | |
| | LED Number | 2 |
| | Range | - 50 m |
| | Smart IR | yes (software support) |
| | Interfaces | |
| | Audio Input/Output | 1 x Jack (3.5 mm)/- |
| | Audio input/Output Network Interface | 1 x Jack (3.5 mm)/- 1 x Ethernet - RJ-45 interface, 10/100 Mbit/s |
| | Network Interface Memory Card Slot | |
| | | microSD - capacity up to 256GB |
| | Installation parameters | |
| | Dimensions (mm) | with bracket: 81 (W) x 81 (H) x 220 (L) |
| | Weight | 0.7 kg |
| | Degree of Protection | IP 67 (details in the user's manual) |
| | Power Supply | 12 VDC, PoE (IEEE 802.3af, Class 3) |
| | Surge protection | TVS 4000 V |
| | Power Consumption | 6 W, 9 W (IR illuminator on) |
| | | |
| | Operating Temperature | |
| | Operating Temperature Humidity | -30°C ~ 60°C -30°C ~ 60°C max. 95%, relative (non-condensing) |

The camera creates a fully functional face recognition system when used with selected NOVUS IP 6000 series recorders (models with "F" in the name).