

6 MPX Bullet IP Camera with white light and IR illuminator

NVIP-6H-6201/WL

6000 VSS

FUNCTIONS



COMPLIANCE

KEY FEATURES

•Resolution: 6 MPX •Lens: fixed focal, f=2.8 mm/F1.6 +Human/Vehicle Object Classification •D/N function - IR cut filter •Video content analysis based on Deep Learning •microSD card support •WDR with double scan sensor •Min. Illumination from 0.008 lx •IR LED, range up to 30 m •white LED illuminator, range up to 30 m

DIMENSIONS





75 mm



170 mm



All camera stream resolutions are supported by NVRs with firmware version 1.4.10 or higher.

Image Image Sensor	6 MPX CMOS sensor 1/2.5" SmartSens
	0.008 lx/F1.6 - color mode,
Min. Illumination	0 lx (IR on) - B/W mode
Electronic Shutter	auto/manual: 1/4 s ~ 1/100000 s
Digital Slow Shutter (DSS)	up to 1/4 s
Nide Dynamic Range (WDR)	yes (double scan sensor), 120dB
Digital Noise Reduction (DNR)	3D
Highlight Compensation (HLC)	yes
Back Light Compensation (BLC)	yes
Reduction of image flicker (Antiflicker)	yes
Lens	
Lens Type	fixed focal, f=2.8 mm/F1.6
DORI	
DORI (Detection, Observation, Recognition, Identification)	for f = 2.8mm - D: 69m, O: 28m, R: 14m, I: 7m
Day/Night	
Mode	day/night switching: mechanical IR cut filter
Switching Mode	auto, manual, time
Switching Level Adjustment	yes
Switching Delay	2 ~ 6000 s
Switching Schedule	yes
Network	
Stream Resolution	3200 x 1800 (QHD+), 2688 x 1520, 1920 x 1080 (Full HD), 1280 x 720 (HD), 704 x 576, 640 x 480 (VGA),
	352 x 288 (CIF), 480 x 240
Frame Rate	30 fps for other resolutions
Multistreaming Mode	number of streams: 3
/ideo/Audio Compression	H.264, H.264+, H.265, H.265+, MJPEG/G.711
Number of Simultaneous Connections	max. 6
Bandwidth	24 Mb/s in total
Network Protocols Support	HTTP, IPv4, IPv4/v6, UDP, HTTPS, FTP, DHCP, DDNS, NTP, RTSP, RTP, UPnP, SNMP, QoS, IEEE 802.1X, PPPoE SMTP, RTCP, P2P, HTML5, RTMP
DNVIF Protocol Support	Profile G/S/T
	from Internet Explorer, Edge, Firefox, Chrome, Opera browser
Camera Configuration	languages: Polish, English, and others
Compatible Software	NOVUS MANAGEMENT SYSTEM VSS, NOVUS MANAGEMENT SYSTEM AC, N Control 6000
Mobile applications	ipGO 6 (iPhone, Android)
Video Analytics	
Functions	abandoned object, object disappearance, line cross, scene change, video blurred, video color cast, objects distinguishing, intrusion detection, smart motion detection with objects distinguishing
Other functions	usungusining, inclusion detection, sinare motion detection with objects distinguishing
Privacy Zones	4 video mask type: single color
Privacy Zones Motion Detection	
Region of interest (ROI)	yes 8
	o 90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal
Image Processing	90 image rotation, 180 image rotation, snarpening, mirror effect, corridor mode, vertical hip, horizontal flip
Prealarm/Postalarm	up to 6 s/up to 120 s
	up to 6 s/up to 120 s e-mail with attachment, saving file on FTP server, saving file on SD card
System Reaction to Alarm Events	
System Reaction to Alarm Events Restoring default settings	e-mail with attachment, saving file on FTP server, saving file on SD card
System Reaction to Alarm Events Restoring default settings IR LED	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software
System Reaction to Alarm Events Restoring default settings IR LED LED Number	e-mail with attachment, saving file on FTP server, saving file on SD card
Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Smart IR	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m
System Reaction to Alarm Events Restoring default settings LED Number Aange Smart IR	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1
System Reaction to Alarm Events Restoring default settings LED Number Aange Smart IR White light illuminator	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support)
System Reaction to Alarm Events Restoring default settings ER LED LED Number Range Smart IR White light illuminator LED Number	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support) 1, warm white color
System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Smart IR White light illuminator LED Number Range	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support)
System Reaction to Alarm Events Sestoring default settings RED LED Number Ange Smart IR Mihte light illuminator LED Number Ange	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support) 1, warm white color
System Reaction to Alarm Events Sestoring default settings RED LED Number Ange Smart IR LED Number Ange Smart Light Illuminator LED Number Ange	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support) 1, warm white color 30 m yes (software support)
System Reaction to Alarm Events Sestoring default settings RED LED Number Ange Smart IR LED Number Ange Smart Light Illuminator LED Number Ange	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support)
System Reaction to Alarm Events Sestoring default settings R LEO LED Number Ange Smart IR Mihte ilght illuminator LED Number Ange Smart Light Interfaces	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support) 1, warm white color 30 m yes (software support) 1 x (ack (3.5 mm)/-
System Reaction to Alarm Events Sestoring default settings ER LED LED Number Aange Smart IR LED Number Aange mart Light Interfaces Audio Input/Output.	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support) 1, warm white color 30 m yes (software support) 1, y Jack (3.5 mm)/- butil-in microphone
System Reaction to Alarm Events Reactioning default settings IR LED LED Number Aange Smart IR LED Number ELED Number ELED Number Smart Light Illuminator LED Number Aange Smart Light State Interfaces Audio Input/Output Network Interface Memory Card Slot	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 30 m yes (software support) 1, warm white color 30 m yes (software support) 1 x jack (3.5 mm)/- builti-n microphone 1 x Ethermet - RJ-45 interface, 10/100 Mbit/s
System Reaction to Alarm Events Reactioning default settings IR LED LED Number Aange Smart IR LED Number LED Number Aange Smart Light Illuminator LED Number Smart Light Summer Aange Audio Input/Output Network Interface Memory Card Slot Installation parameters	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support) 1, warm white color 30 m yes (software support) 1 x fack (3.5 mm)/- built-in microphone 1 x Kinner Ry-45 interface, 10/100 Mbit/s microSD - capacity up to 256GB
System Reaction to Alarm Events Reaction default settings IR LEO LEO Number Aange Smart IR Uhite Jight Illuminator LEO Number Aange Smart Light Interfaces Audio Input/Output Network Interface Memory Card Slot	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support)
System Reaction to Alarm Events Restoring default settings RetED LED Number Aange Smart IR LED Number Aange Smart Light Illuminator LED Number Aange Smart Light Component of the set of th	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 3 on yes (software support)
System Reaction to Alarm Events Reaction default settings IR LEO LEO Number Aange Smart IR Uhite Jight Illuminator LEO Number Aange Smart Light Interfaces Audio Input/Output Network Interface Memory Card Slot	e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 1 30 m yes (software support)

NoVus

Power Supply	12 VDC, PoE (IEEE 802.3af, Klasa 3)
Surge protection	TVS 4000 V
Power Consumption	4 W, 6.5 W (IR illuminator on), 7 W (white light illuminator on)
Operating Temperature	-30°C ~ 60°C
Humidity	max. 95%, relative (non-condensing)