

32-channel IP Recorder

NVR-6432-H2/F-II





FUNCTIONS



The recorder is dedicated to work with NOVUS 6000 series IP cameras. Detailed data can be found in the compatibility table available in the DOWNLOADABLE FILES tab.

























KEY FEATURES

- •32 x video and audio channels
- •Recording speed up to 960 fps at 4000 x
- •Recorded stream size: 320 Mb/s in total from all cameras
- •2 x internal place for HDD mounting •3 x monitor outputs (HDMI 4K UltraHD,

- HDMI, VGA)
 •RACK mount
- Face recognition

DIMENSIONS







Power Consumption

וח		
	Video	
	IP Cameras	up to 32 channels at 4000 x 3000 resolution (video + audio)
	Maximum Supported Camera Resolution	4000 x 3000
fps EC	Compression	H.264, H.265, H.265 Smart
	Monitor Output	main (split screen, full screen, sequence): 1 x HDMI (4K UltraHD), 1 x VGA (up to 2 monitors simultaneously) spot: $1 \times \text{HDMI (FullHD)}$
	Dualstreaming Support	yes
	Fisheye Support	yes, 6000 IP series cameras using any web browser, N-VID6, N Control 6000
	Audio	asing any wea arouser, it-vibo, it control occo
	Audio Input/Output	1 x line-in (RCA) / 1 x line-out (RCA), 1 x HDMI
	Recording	1 X IIII CHA / 1 X III COUL (NOA), 1 X TIDAII
	Stream Size	320 Mb/s in total from all cameras
		continuous, triggered by: manual, alarm input, motion detection, face recognition, intelligent image analysis
	Recording Mode	functions
	Prealarm/Postalarm	up to 5 s/up to 600 s
	Display	
	Display Speed	960 fps (32 x 30 fps)
	Playback	
	Playback Speed	480 fps (16 x 30 fps)
	Recorded Data Search	by date/time, events, image analysis events, POS, motion in a defined area, related to face recognition, tags, license plate number
	Backup	
	Backup Methods	USB port (HDD or Flash memory), network
	Backup File Format	MP4, AVI, RPAS (player included)
	Storage	
	Internal Storage	available mount: 2 x HDD 3.5" 10 TB SATA
x	Total Internal Capacity	20 TB
^	Alarm	
	Internal Alarm Input/Output	8/4 relay type
	Camera Alarm Input/Output	supports IP camera's alarm input/output
	Motion Detection	supports camera's motion detection
	System Reaction to Alarm Events	buzzer, alarm output activation, recording activation, PTZ, e-mail with atatchment, Full Screen, PUSH message, voice prompt, snapshot
	Intelligent image analysis	
	Supported Functions	Exception, Scene Change, Video Blurred, Video Color Cast, Tripwire, Zone entrance, Abandoned Object, Object Disappearance, Face Recognition, Perimeter Intrusion Detection by pedestrian or yehicle, Line Cross
53 mm		Object Disappearance, Face Recognition, Perimeter Intrusion Detection by pedestrian or vehicle, Line Cross Detection by pedestrian or vehicle, License Plate Recognition (LPR)
	Database Capacity	10000 faces 50000 license plates
	Other parameters	face recognition for 6 NOVUS 6000 series IP cameras with 'F' in the model name or 2 ONVIF cameras
	Network	
	Network Interface	2 x Ethernet - RJ-45 interface, 10/100/1000 Mbit/s
	Network Protocols Support	HTTP, TCP/IP, IPv4/v6, HTTPS, FTP, DHCP, DNS, DDNS, NTP, RTSP, UPnP, SNMP, IEEE 802.1X, PPPoE, SMTP, P2P, POS, HTML5
	PC/MAC Software	NOVUS MANAGEMENT SYSTEM VSS, NOVUS MANAGEMENT SYSTEM AC, NMS, Internet Explorer, Firefox, Chrome, Opera, N Control 6000, Edge/Safari, N Control 6000
	Mobile applications	N-VID6 (iPhone, Android)
	Number of Simultaneous Connections	up to 128 clients, up to 36 main streams or 128 substreams or 32 playback streams in total
†	Bandwidth	256 Mb/s in total to all client workstations
268 mm	PTZ	
	PTZ Functions	pan/tilt/zoom, preset commands
	Auxiliary Interfaces	
	USB Ports	2 x USB 2.0, 1 x USB 3.0
	Operating system	
	Operating System	Linux
	OSD	languages: Polish, English, others
	Control	PC mouse and IR remote controller (in-set included), network
	System Diagnostic Security	automatic control of: HDDs, network, camera connection loss password protection, IP filtering, MAC filtering, ARP guard
	Installation parameters	password protection, if intering, MAC littering, AKF guard
	Dimensions (mm)	380 (W) x 53 (H) x 268 (D)
	Dimensions (mm) Weight	1.5 kg (without HDD)
	Power Supply	12 VDC (100 ~ 240 VAC/12 VDC PSU in-set included)

The availability of individual functions (including image analysis) depends on the model of the cameras used, as well as the software version of the recorder and cameras. In order to create face recognition system, please deploy MOVIS 6000 series if cameras with "F" in the model name. Presented display and playback speeds are achieved using dual-streaming. Detailed data on hard drives can be found in the compatibility table available in the DOWNLOADABLE FILES tab.

40 W (with 2 HDDs) -10°C ~ 50°C