



## IP User monitor

NVE-MV107WIFI-W



### FUNCTIONS

IPS

NVE-MV107WIFI villa user monitor is an elegant and aesthetically made device designed for installation in a residential or office. A large 7" color screen and an intuitive menu allows quick and convenient use of its functions. In addition to the basic functions (camera image display, door opening), the on-screen menu also allows you to view and delete voice messages, photos and videos as well as play music. Internal memory of the device allows you to save up to 100 photos. The built-in loudspeaker and microphone facilitate operation and communication with the guest. Communication with another user is also possible thanks to the intercom function. The optionally connection of eight cameras can create a simple VSS system enriched with motion detections.

Included:

- IP User monitor
- wall bracket compatible with electric box 60 mm
- 2x fixing screws and expansion bolts
- RJ45 adapter with cable
- short manual

Device type	IP Indoor monitor
Display	LCD TFT
Resolution	1024 x 600 px
Diagonal	7"
Video coding	H.265 (default); H.264
Power supply input	15 V DC
PoE	48 V DC (802.3af)
Power consumption	530mA 8 W (Max.)
Ringbell output	NO Relay (4 A / 36 V DC/AC)
Port LAN	1 x 10M / 100M Ethernet
Wi-Fi	Dual Band 2,4 GHz/5 GHz (IEEE 802.11 a/b/g/n)
Additional functions	SD card slot, volume control, monitoring of the view from cameras, intercom calls, voice mail, photos and video recording, mobile application via WIFI, doorbell, Status LED
Dimensions	188 x 136 x 22 mm
Weight	380g
Operating temperature	from -10 to 50 °C
Color	Signal White (RAL9003)