NOVUS

2-WIRE IP User monitor

NVE-2W-MV108WIFI-W





FUNCTIONS



NVE-2W-MV108WIFI-W villa user monitor is an elegant and aesthetically made device designed for installation in a residential or office. A large 8 "color screen and an intuitive menu allows quick and convenient use of its functions. In addition to the basic functions (camera image display, door opening), the on-screen menu also allows you to view and delete voice messages, photos and videos as well as play music. Internal memory of the device allows you to save up to 100 photos. The built-in loudspeaker and microphone facilitate operation and communication with the guest. Communication with another user is also possible thanks to the intercom function. The optionally connection of eight cameras can create a simple VSS system enriched with motion detections.

Included:

- 2-WIRE IP User monitor
- wall bracket compatible with electric box 60 mm
- 2x fixing scerws and expansion bolts
- short manual

Device type	2-WIRE IP Indoor monitor
Display	IPS
Resolution	1280 x 800 px
Diagonal	8"
Video coding	H.265 (default); H.264
Power supply input	24 - 36 VDC
Power consumption	8 W (Max.)
Wi-Fi	Dual Band 2,4 GHz/5 GHz (IEEE 802.11 a/b/g/n)
Additional functions	SD card slot, volume control, monitoring of the view from cameras, intercom calls, voice mail, photos and video recording, mobile application via WIFI, doorbell
Dimensions	200 x 148 x 20 mm
Weight	410g
Operating temperature	from -10 to 50 °C
Color	Signal White (RAL9003)